

# **HPT371 UDMA/ATA133 Controller**

## **Turbo Linux 6.0**

### **Installation Guide**

Version 1.0

Copyright © 2001 HighPoint Technologies, Inc.

All rights reserved.

Last updated on Jan 7, 2002

## Table of Contents

---

<b>1 Overview.....</b>	<b>1</b>
<b>2 Installing Turbo Linux on HPT371.....</b>	<b>1</b>
Step 1 Prepare Your Hardware for Installation .....	1
Step 2 Check System BIOS Settings.....	1
Step 3 Prepare the Driver Diskette.....	1
Step 4 Install Turbo Linux.....	2
<b>3 Installing HPT371 Driver on an Existing System.....</b>	<b>2</b>
Step 1 Obtain the Driver Module.....	2
Step 2 Test the Driver Module .....	3
Step 3 Configure System to Automatically Load the Driver.....	3
Step 4 Configure System to Mount Volumes when Startup .....	5
<b>4 Monitoring the Driver.....</b>	<b>5</b>
Checking Devices Status.....	5
<b>5 Updating the Driver.....</b>	<b>5</b>
<b>6 Uninstalling.....</b>	<b>6</b>
Uninstalling the Driver.....	6

# 1 Overview

The purpose of this document is to provide clear instructions on how to install and use HPT371 UDMA/ATA133 controllers on a Turbo Linux 6.0 system.

## 2 Installing Turbo Linux on HPT371

If you would like to install Turbo Linux onto drives attached to HPT371 controller, please perform the following operations:

### Step 1 Prepare Your Hardware for Installation

After you attach your hard disks to HPT371 controller, you can use HPT371 BIOS Setting Utility to configure your hard disks.

Before installation, you must remove all the disk drives, which are not physically attached to HPT371 controller, from your system.

#### Note

---

If you have other SCSI adapters installed, you must make sure the HPT371 controller BIOS will be loaded firstly. If not, try to move it to another PCI slot. Otherwise you may be unable to boot up your system.

---

### Step 2 Check System BIOS Settings

In your system BIOS SETUP menu, change **Boot Sequence** in such a way that the system will first boot from floppy or CDROM, and then from SCSI. Refer to your BIOS manual to see how to set boot sequence.

If your BIOS settings do not support such a boot sequence, you can first set it to boot from floppy or CDROM. After you finish installation, set SCSI as the first boot device to boot up the system.

### Step 3 Prepare the Driver Diskette

The driver diskette is provided as an image file, **turbodd.img**.

On a DOS or Windows system, you can make the diskette using rawrite.exe. It can be found on the Turbo Linux CD (under /dosutils). Just run it under a command window and follow its prompt.

On a Linux system, you can use the “dd” command to make the boot diskette. Insert a floppy disk into the floppy drive and type the command:

```
# dd if=turbodd.img of=/dev/fd0
```

## Step 4 Install Turbo Linux

- 1) Start installing Turbo Linux by booting from the Turbo Linux CD and continue normal installation until you are asked “Do you have any SCSI devices?”.
- 2) Press “**ALT-F2**” to activate the second console. Insert the driver diskette into floppy drive and type in the following commands to load hpt371 module.

```
[TurboLinux Install]$ mkdir /tmp/floppy  
[TurboLinux Install]$ mount /dev/fd0 /tmp/floppy  
[TurboLinux Install]$ /tmp/floppy/install
```

- 3) Press “**ALT-F1**” to return to the installation console and select “**No**” if you do not have any other SCSI controllers installed.
- 4) Continue the installation as normal. You can refer to Turbo Linux installation guide.

---

### Note

The system device mapping order is the same as the order shown in HPT371 BIOS Setting Utility. If you have no other SCSI adapters installed, the device marked as “BOOT” or “HDD0” will be /dev/sda, “HDD1” will be /dev/sdb, “HDD2” will be /dev/sdc, etc. When creating mount points, you must mount /boot on /dev/sda.

---

- 5) When system prompts “What format does your system keep time in?”, press “**Alt-F2**” to switch to the second console again and type in the following command:

```
[TurboLinux Install]$ /tmp/floppy/install
```

When asked, enter the number of the kernel you have selected to install. Then press “**Alt-F1**” to switch to installation console and finish installation as normal.

## 3 Installing HPT371 Driver on an Existing System

If you are currently running Linux and would like to access drives or arrays attached to the HPT371 Controller, you can perform the following steps.

---

### Note

If you use a SCSI adapter to boot your system, you must make sure the HPT371 controller BIOS will be loaded after that adapter’s BIOS. If not, try to move it to another PCI slot. Otherwise you may be unable to boot up your system.

---

## Step 1 Obtain the Driver Module

Turbo Linux 6.0 may use different kernel versions. You must first check your system to find which kernel it uses, and get the corresponding driver module for it. On the driver

diskette there are driver modules for different kernel versions. They are listed as below:

hpt371i386.o	Driver for i386 kernel
hpt371i586.o	Driver for i586 kernel
hpt371i686.o	Driver for i686 kernel
hpt371i386smp.o	Driver for i386 SMP kernel
hpt371i586smp.o	Driver for i586 SMP kernel
hpt371i686smp.o	Driver for i686 SMP kernel

After copying the proper driver module, rename it to hpt371.o.

## Step 2 Test the Driver Module

You can test out the module to ensure that it works for your system by typing in "**insmod hpt371.o**".

Sometimes insmod will report "**unresolved symbols**" when you attempt to load the module. This can be caused by two ways:

1) If your system is using a kernel which has not built-in SCSI support, you must load the SCSI module before load hpt371.o. Try to load SCSI modules first.

E.g.           # **insmod scsi\_mod**  
              # **insmod sd\_mod**  
              # **insmod hpt371.o**

2) If you recompile the kernel with SCSI support and still receive the "**unresolved symbols**" error, it may be caused that you have not configured symbol versioning correctly. To correct it, recompile the kernel with symbol versioning configured. Please refer to the kernel documents for more information.

To ensure the module has been loaded successfully, you can check the driver status by typing in the command "**cat /proc/scsi/hpt371/X**", where **X** is the filename you found under /proc/scsi/hpt371/. You should see the driver banner and a list of attached drives. You can now access the drives as a SCSI device (the first device is /dev/sda, then /dev/sdb, etc.).

### Example

---

If you have one disk attached to HPT371, it will be registered to system as device **/dev/sda**. You can use "**fdisk /dev/sda**" to create a partition on it, which will be **/dev/sda1**, and use "**mkfs /dev/sda1**" to setup a file system on the partition. Then you can mount **/dev/sda1** to somewhere to access it.

---

## Step 3 Configure System to Automatically Load the Driver

Most likely, you will not want to type in "**insmod hpt371.o**" each time you boot up the system. Therefore you must install the module and tell the system about it. To install the

module, type in the following commands (first change directory to where the proper hpt371.o can be located):

```
# install -d /lib/modules/2.2.13-18/scsi
# install -c hpt371.o /lib/modules/2.2.13-18/scsi
```

If you are using SMP version kernel, you should use

```
# install -d /lib/modules/2.2.13-18smp/scsi
# install -c hpt371.o /lib/modules/2.2.13-18smp/scsi
```

Then you should inform the system when to load the module.

1. If you have no other SCSI adapters installed, you can edit the file `"/etc/modules.conf"` and add the following line:

```
probeall block-major-8 scsi_mod sd_mod hpt371
options -k hpt371
```

This tells the kernel to try loading the SCSI and hpt371 modules whenever it tries to access a SCSI device `/dev/sd[a-z]`. If you have SCSI support compiled in kernel, you may remove the `"scsi_mod"` and `"sd_mod"` from that line.

The line `"options -k hpt371"` ensures the module will not be autocleaned.

#### Notice

---

Upon your system configuration the modules configuration file may be another file, possibly deprecated `"conf.modules"` file. You may have to check which configuration file you use and modify the correct one.

---

2. If you use a SCSI adapter to boot the system, you cannot do as above since this may conflict with other SCSI devices. However, you can add the driver to the existing RAM disk image. First check which image file you are using by checking the `"initrd="` line in file `/etc/lilo.conf`, then use the following commands (we assume the file is `/boot/initrd`):

```
# gzip -dc /boot/initrd > /tmp/initrd.ext2
# mkdir /mnt/initrd
# mount -o loop /tmp/initrd.ext2 /mnt/initrd
# cp hpt371.o /mnt/initrd/lib/ (specify the correct location of hpt371.o here)
# echo "insmod /lib/hpt371.o" >> /mnt/initrd/linuxrc
# umount /mnt/initrd
# gzip -c /tmp/initrd.ext2 > /boot/initrd
# lilo
```

Then reboot your system and the driver will be loaded.

Now, reboot the system and try to type in the command `"fdisk /dev/sda"`. The kernel should automatically load the HPT371 driver.

## Step 4 Configure System to Mount Volumes when Startup

Now you can inform the system to automatically mount the array by modifying the file `/etc/fstab`. E.g. You can add the following line to tell the system to mount `/dev/sda1` to location `/mnt/hpt` after startup:

```
/dev/sda1      /mnt/hpt      ext2    defaults    0 0
```

## 4 Monitoring the Driver

Once the driver is running, you can monitor it through the Linux `proc` file system support. There is a special file under `/proc/scsi/hpt371/`. Through this file you can view driver status and send control commands to the driver.

### Note

---

The file name is the SCSI host number allocated by OS. If you have no other SCSI cards installed, it will be 0. In the following sections, we will use X to represent this number.

---

### Checking Devices Status

Using the following command to show driver status:

```
# cat /proc/scsi/hpt371/X
```

This command will show the driver version number, physical device list and logical device list.

## 5 Updating the Driver

If you are not booting from disks attached to HPT371 controller, you can update the driver just by reinstalling it following the previous section, "**Installing Driver on an Existing System**".

If you are using a system installed to HPT371 controller, you can update the driver by the following steps.

- 1) First obtain the new driver module file `hpt371.o`. Refer to the previous section "**Obtain the Driver Module**". In the following steps, we assume you have copied it to `/tmp/hpt371.o`.
- 2) Replace `hpt371.o` in the boot RAM disk image.

```
# cp /boot/initrd /boot/initrd.bak
# gzip -dc /boot/initrd > /tmp/initrd.ext2
# mkdir /mnt/initrd
# mount -o loop /tmp/initrd.ext2 /mnt/initrd
# cp /tmp/hpt371.o /mnt/initrd/lib/hpt371.o
# umount /mnt/initrd
# gzip -c /tmp/initrd.ext2 > /boot/initrd
```

- 3) Use "**lilo**" to reinstall the RAM disk:

```
# lilo
```

- 4) Update hpt371.o in /lib/modules:

```
# cp /tmp/hpt371.o /lib/modules/2.2.13-18/scsi/hpt371.o
```

If you are using SMP version kernel, use

```
# cp /tmp/hpt371.o /lib/modules/2.2.13-18smp/scsi/hpt371.o
```

- 5) Reboot your system to make the new driver take effect.

## 6 Uninstalling

### Uninstalling the Driver

You can only uninstall the driver when your system is not booting from devices attached to HPT371 controller. Just remove the lines you added to /etc/modules.conf and /etc/fstab.