

# PC Speakers with FM Radio and Integrated Clock

- FM radio, can also be used without PC
- Stylish clock
- Active 6 Watts RMS stereo speaker system
- Bass reflex system gives class leading bass performance
- Headphone connection
- Magnetically shielded to prevent distortion of the monitor



MMS223/00





## **6 Watts RMS Harmonic Pulse**



#### **Specifications:**

Amplifier Output Power 2 x 3 W RMS at 10% THD

#### Frequency Response: 120 Hz – 20 kHz

**Speakers:** 2 x 3" (7.5 cm) drivers Both magnetically shielded

#### Cables

Audio in cable: 3.5 mm jack (fixed on active satellite), length 1.3 m Signal connector cable (between the two speakers), length 1.5 m  $\,$ 

#### **Features on Active Satellite**

FM radio with On/Off button and LED indicator Master On/Off button with LED indicator Rotary volume wheel Headphone socket (3.5 mm)

#### **Dimensions**

Retail Packaging: (H  $\times$  W  $\times$  D) = 232  $\times$  275  $\times$  120 mm

#### Quantity

Products per Mastercarton: 5 Products per Pallet: 240 Products per 40' container: 5,040

#### Weight

Gross weight of retail packaging: 2.72 kg

12NC / EAN	MMS223/00:	MMS223/00S:
12NC	9306 000 00092	9082 100 02935
EAN single product	87 10895 530620	87 10895 816816
EAN master carton	87 10895 530682	87 10895 816823

#### **System Requirements**

Preferred: Stereo sound card or multichannel soundcard with 2 channel output mode

Other possibilities: Stereo source such as MP3/CD/Cassette player, game consoles, TV.

#### Warranty

2 Year warranty

More information about Philips Multimedia products including a complete range of multimedia speaker systems, as well as the award winning Edge series of Soundcards can be found at: www.philips.com/sound (Europe) www.philips.com/ce



Easy Controls



FM Radio



LCD Clock

### **Philips BCU Peripherals & Accessories**

Specifications are subject to change without notice © 2003 Royal Philips Electronics N.V. All rights reserved

